

DIGITAL MULTIMETER



- **Article code DIG-MM1**
- 3 ½ digit LC and bar graph display with polarity and battery low voltage indication.
- For voltage, DC current and resistance measurements, continuity and diode testing.
- DC voltage : 320 mV / 600 V (5 ranges)
- Accuracy : ± 0.5 % + 2 digit
- AC voltage : 3.2 V / 600 V (4 ranges)
- Accuracy : ± 1.5 % + 5 digit
- DC current : 320 µA / 3200 µA (2 ranges)
- Accuracy : ± 1.0 % + 2 digit
- Resistance : 320 Ω / 32MΩ (6 ranges)
- Accuracy : 320 Ω : ± 1.0 % + 4 digit
3.2 kΩ – 3.2 MΩ : ± 0.8 % + 2 digit
32 MΩ : ± 2.0 % + 5 digit
- Continuity test : 20 Ω
- Diode test : 1.5 mA
- All measures with overload protection